

ADC® Pocket Diagnostic Instruments

Use, Care and Maintenance



ADC[®]
AMERICAN DIAGNOSTIC CORPORATION

Thank you for choosing an ADC® Diagnostic set. We're proud of the care and quality that goes into the manufacture of each and every diagnostic instrument that bears our name. Every component has been carefully designed to maximize performance. This booklet refers to both Otoscope and Ophthalmoscope sets (Models 5110N, 5110E, 5111N, 5112N).

Device Description and Intended Use

Ophthalmoscope attachment (5110N, 5110E, 5112N)

The ophthalmoscope is a hand held, battery-powered device containing illumination and viewing optics intended to examine the media (cornea, aqueous, lens, and vitreous), the retina, blood vessels, optic nerve, and other structures of the eye. It is intended to be used by a trained healthcare professional.

Otoscope Attachment (5110N, 5110E, 5111N)

A handheld battery powered device with magnifying system that provides illumination of the ear canal and tympanic membrane.

Latex Statement - This device and all accessories are latex free.

This device should be used by a trained healthcare professional.

Contraindications

The use of this device is contraindicated in patients who have already received prolonged or intense light exposure, especially if the patients are infants, aphakes, or persons with diseased eyes. Excessive exposure to light may result in patient injury. See warnings for additional information.

General Warnings

A warning statement in this manual identifies a condition or practice which, if not corrected or discontinued immediately, could lead to patient injury, illness, or death.

CAUTION: Because prolonged intense light exposure can damage the retina, the use of the device for ocular examination should not be unnecessarily prolonged, and the brightness setting should not exceed what is needed to provide clear visualization of the target structures.

The retinal exposure dose for a photochemical hazard is a product of the radiance and the exposure time. If the value of radiance were reduced in half, twice the time would be needed to reach the maximum exposure limit.

While no acute optical radiation hazards have been identified for direct or indirect ophthalmoscopes, it is recommended that the intensity of light directed into the patient's eye be limited to the minimum level which is necessary for diagnosis. Infants, aphakes and persons with diseased eyes will be at greater risk. The risk may also be increased if the person being examined has had any exposure with the same instrument or any other ophthalmic instrument using a visible light source during the previous 24 hours. This will apply particularly if the eye has been exposed to retinal photography.

CAUTION: Do NOT immerse the battery handle in liquid. Consult the cleaning and disinfection instructions for each part for further information about cleaning and disinfecting this product. Never clean or disinfect any device with batteries in it.

CAUTION: Federal law restricts this device to sale by or on the order of a physician or licensed health-care practitioner.

WARNING: The carrying cases provided with these devices are intended for long term storage or transport between facilities or when shipping devices to and from ADC's facility for repair or servicing. Carry cases

(including internal liners) can NOT be cleaned or disinfected and should be safely discarded if contaminated. Do not carry the case into a contaminated environment.

WARNING: When replacing lamp, allow lamp to cool for five minutes before handling.

WARNING: No form of sterilization has been validated for this device or its corresponding components and sterilization may compromise the safety and effectiveness of this device. (This includes steam sterilization.)

WARNING: Do NOT place devices or accessories back into carrying case after use on a patient without first cleaning/disinfecting the device/accessories as described in the cleaning and disinfection section of this manual. Carry case liners can NOT be cleaned or disinfected and should be discarded if contaminated.

WARNING: Use of any accessories or materials not indicated in the user's manual can degrade the minimum safety of the equipment.

WARNING: Only replace listed accessories (attachments), lamps, or batteries for the device.

WARNING: During use metal components near instrument head can become warm. This is especially true if device is on for extended periods of time. Do not leave device on when not in use.

Otoscope Parts and Assembly

The Pocket Otoscope consists of a "AA" battery handle (#5160N), fiberoptic Otoscope Instrument Head (5120N), with attached movable viewing lens, and disposable specula (2.75mm and 4.25mm).



Removing and Attaching the Instrument Head

Pocket otoscope heads are threaded and can be removed by rotating the threaded connection counterclockwise, or attached by rotating the threaded connection clockwise.



Viewing Lens

To move during an examination, turn the lens bezel clockwise to lift up. To reposition, reverse procedure.



Attaching the Disposable Specula

Push the flanged end of the desired speculum onto the chrome socket and twist counterclockwise to engage. Reverse procedure to remove and discard after each use.



Pneumatic Otoscope

To perform, insert tapered end of insufflator fitting (5121N) sold separately, into hole on side of Otoscope head. Attach optional bulb assembly (5122N) sold separately.

Ophthalmoscope Parts and Assembly



The Pocket Ophthalmoscope consists of a "AA" battery handle (5160N) and Ophthalmoscope instrument head (5140N) with xenon illumination.

Aperture Selection

This unit is equipped with 5 internal apertures - small, large, semi-circle, red-free, and fix-

ation. To select, rotate the aperture selection wheel at the front of the instrument head.



Corrective Lens Selection

This unit is equipped with 19 corrective lenses from +20 to -20 diopters (negative lenses in red). To select, rotate the corrective lens selection wheel at either side of the instrument head. Selected lenses can be viewed in the lighted panel on practitioner side of instrument



OFF
ON

Turning Instrument On

To illuminate, slide the on/off switch located on the battery handle pocket clip away from the instrument head. Slide the switch in the opposite direction to turn off.



Replacing Xenon Lamp


Remove the Instrument head by turning counterclockwise. Grab end of lamp from inside base of instrument head and remove. Replace with new lamp, taking care not to touch glass, and align lamp metal guides on side of lamp with grooves in lamp socket.



NOTE: Allow lamp to cool for five minutes before handling if device has been recently used. (Otoscope lamp p/n 5111N-4, Ophthalmoscope lamp p/n 5112N-4)

Battery Replacement

This unit requires 2 "AA" batteries. For best performance, we suggest alkaline batteries. To replace, remove the battery cap at the base of the handle by turning counterclockwise and replace batteries, taking care to observe correct polarity. **NOTE:** This instrument should be turned OFF when not in use. If storing for extended lengths of time, remove batteries completely.



Handle Care and Maintenance

Periodically check the condition of both the batteries, making sure there is no sign of corrosion or oxidation. Always replace BOTH batteries. Alkaline batteries are recommended. Remove batteries from handle if instrument will not be used for an extended period of time.

Cleaning and Disinfection

Basic Cleaning Procedure for Battery Handles, Otoscope and Ophthalmoscope Heads

To clean the exterior of the device, prepare a 70% isopropyl alcohol solution and soak a lint-free cloth. Wipe down the exterior of the ophthalmoscope head and handle, cleaning all external surface areas. Care should be taken to prevent excess liquid from seeping into the components.

Isopropyl alcohol may be substituted with commonly used, EPA-registered hospital disinfectant wipes for cleaning purposes if desired. Please refer to the directions provided by the manufacturer of the wipes for appropriate instructions for use to ensure effective contact time between the wipe and the device.

It is important to note that solution residue on the magnifying lenses may decrease device performance. All excess cleaning fluids must be carefully wiped clean if these surfaces are cleaned. The lenses of the instrument head may be cleaned with a lint-free cloth or lens paper.

Disposable Specula Cleaning/Disinfection Instructions

Disposable specula should not be cleaned or disinfected in any way. Disposable specula are single patient use only and must be discarded after use. Disposable specula should not be used if they appear to be visibly contaminated or have accidentally come into contact with contaminated materials prior to use.

Troubleshooting

The following guidelines should be used to determine if your device has reached its end of life or requires servicing. If the corrective actions described in this section do not resolve your issues, please see the warranty section of this manual to have your device serviced.

Otoscope and Accessories Troubleshooting Guide

Trouble Area	Possible Cause	Corrective Action
No light output	Lamp burned out Wrong lamp installed Batteries are depleted	Replace the lamp with ADC part #5111N-4 Replace the lamp with ADC part #5111N-4 Replace with fresh "AA" batteries
Instrument head will not connect	Thread/connection is damaged	Service required
Specula will not attach properly	Wrong specula used Specula mount is damaged	Use only Welch Allyn brand or compatible Service required
Loose or misaligned magnifying lens	Lens mount is damaged	Service required
Poor or obstructed view through lens	Lens is dirty Lens is damaged	Clean with lint free cloth Service required
Dim light output	Lamp near end of useful life Batteries are depleted	Replace the lamp with ADC part #5111N-4 Replace with fresh "AA" batteries
Visible corrosion on instrument or accessories	Damage from excessive moisture	Service required



Do not dispose of this product as unsorted municipal waste. Prepare this product for reuse or separate collection as specified by Directive 2002/96/EC of the European Parliament and the Council of the European Union on Waste Electronic and Electrical Equipment (WEEE). If this product is contaminated, this directive does not apply.

LIMITED WARRANTY

American Diagnostic Corporation (ADC®) warrants its products against defects in materials and workmanship under normal use and service as follows:

1. Warranty service extends to the original retail purchaser only and commences with the date of delivery.
2. The optical system is warranted for one year.

What is Covered:

Repair, or replacement of parts, and labor.

What is Not Covered:

Transportation charges to and from ADC®. Damages caused by abuse, misuse, accident, or negligence. Incidental, special, or consequential damages. Some states do not allow the exclusion or limitation of incidental, special, or consequential damages, so this limitation may not apply to you.

To Obtain Warranty Service:

Send item(s) postage paid to ADC®, Attn: Repair Dept., 55 Commerce Dr., Hauppauge, NY 11788. Please include your name and address, phone no., proof of purchase, and a brief note explaining the problem.

Implied Warranty:

Any implied warranty shall be limited in duration to the terms of this warranty and in no case beyond the original selling price (except where prohibited by law). This warranty gives you specific legal rights and you may have other rights which vary from state to state.



ADC
55 Commerce Drive
Hauppauge, NY 11788
U.S.A.



ADC (UK) Ltd.
Unit 6, PO14 1TH
United Kingdom

Inspected in the U.S.A.

Made in China
tel: 631-273-9600, 1-800-232-2670
fax: 631-273-9659

www.adctoday.com
email: info@adctoday.com